



## Features:

- 5½ Digit LED
- Calibration of AC Volt, Amp Frequency Meters
- Calibration of DC Volt, Amp Meters
- Calibration of Resistance Meters, Clamp & Multi Meters

## Technical Data:

Output	Range	Accuracy	Turns Ratio	100 / 1	100 / 1
Voltage	250mV, 1V, 2.5V, 5V, 10V, 25V, 50V, 100V, 250V, 500V, 1000V	DCV: $\pm(0.02\%$ of reading +0.01% FS) ACV: $\pm(0.05\%$ of reading +0.02% FS)	Input Max.	5A	10A
			Current	500A	1000A
Current	100 $\mu$ A, 500 $\mu$ A, 2.5mA, 10mA, 25mA, 100mA, 250mA, 1A, 2.5A, 10A, 50A	DCI: $\pm(0.03\%$ of reading +0.02% FS) ACI: $\pm(0.05\%$ of reading +0.03% FS)	Clamp Jaw	> 20mm	> 28mm
			DC Impedence	0.7 $\Omega$	0.9 $\Omega$
Frequency	50Hz, 60Hz, 400Hz, 1kHz	<0.1%	DC Burden	5A / 3.5V	10A / 2.5 V
			AC Burden	5A / 6V	10A / 5V
Resistance	10, 24, 50, 100, 240, 500( $\Omega$ ) 1, 2, 4, 5, 10, 25 (k $\Omega$ ) 10x1k, 24x1k, 50x1k 100x1k, 240x1k, 500x1k, 1kx1k, 2.4kx1k, 5kx1k, 10kx1k, 24kx1k	$\pm(0.2\%$ of reading +20m $\Omega$ )	Frequencies	DC to 60Hz	DC to 60Hz
			Accuracy	$\pm 0.3\%$ rdg	$\pm 0.3\%$ rdg

## Special Function :

Stability	DC : <0.01%FS / 3 min. AC : <0.02%FS / 3 min.
Ripple	<0.2%
Power Supply	230V AC, 50 (60) Hz
Distortion	<0.5%

- Standard Accessories : Key Adjuster, Power Cod, Pair of Output Leads 50A, Briefcase, Optional Accessories Standard Current Coil
- Dimension : 190(L) x 480(W) x 545(H)mm