



DC Current



NCV



AC / DC Voltage



Resistance



Back Light



Diode



Low Battery Indication



Continuity



Over Range Display



600V

FEATURES :

- 3½ DIGIT MANUAL MULTIMETER
- 1,999 COUNT
- DATA HOLD
- TRUE RMS
- NCV
- LIVE WIRE RECOGNITION



DC VOLTAGE

RANGE	RESOLUTION	ACCURACY
200mV	100uV	±0.5% of rdg ±4 digits
2000mV	1mV	
20V	10mV	
200V	100mV	
600V	1V	

DC CURRENT

RANGE	RESOLUTION	ACCURACY
20uA	10nA	±1.0% of rdg±5 digits
2mA	10uA	
200mA	100uA	±2% of rdg±5 digits
10A	10mA	

AC VOLTAGE

RANGE	RESOLUTION	ACCURACY
200V	100mV	±1.0% of rdg±5 digits
600V	1V	

RESISTANCE

RANGE	RESOLUTION	ACCURACY
200Ω	0.1Ω	±0.8% of rdg±5 digits
2KΩ	1Ω	
20KΩ	10Ω	±0.8% of rdg±1 digit
2MΩ	1kΩ	
200MΩ	100kΩ	±1.2% of rdg±5 digits

TRANSISTOR hFE TEST (0-1000)

RANGE	TEST RANGE	TEST CURRENT	TEST VOLTAGE
NPN & PNP	0~1000	1B ≈15μA	VCE≈1.2V

POWER : AAA 1.5V x 2

Dimension	: H140 x W72 x D37 mm
Weight	: Approx.195gms.
Accessories	: Test leads, User Manual & Battery.
Qty	: 50 Pcs. in a Box